

9.2-ch Network AV Receiver

VSX-LX505(B/S)





The VSX-LX505 creates the soundscape of IMAX® Enhanced and Dolby Atmos®/DTS:X ideally calibrated with Advanced MCACC, and even provides similar sound effects with Dolby Atmos Height Virtualizer without additional surround speakers. Enjoy spectacles from next-gen video/gaming standards with support for HDMI 2.1*1 with 8K, VRR, ALLM, QFT pass-through, or stream songs across the house with Multi Zone Music, SONOS system, Chromecast built-in, DTS Play-Fi®, and Apple AirPlay 2. Don't forget it also features Powered Zone 2/Zone 3 Audio, 11.2/5.6/2.8 MHz DSD playback with PCM conversion, 2 HDMI outputs and Roon Tested certification. Finally, it works with Alexa or OK Google for voice control.

AMPLIFICATION

- > Channels: 9
- > Amplification Type: Direct Energy
- 215 W/ch (6 ohms, 1 kHz, THD 10 %, 1ch Driven)
- 180 W/ch (8 ohms, 1 kHz, THD 1 %, 1ch Driven IEC)

AUDIO FEATURES

- > IMAX Enhanced
- Dolby Atmos®, Dolby Surround Upmixer
- DTS:X®, DTS Neural:X® Upmixer
- Reflex Optimizer
- Dolby Atmos Height Virtualizer
- > Dolby® TrueHD, Dolby Digital Plus
- DTS-HD Master Audio, DTS-HD High Resolution Audio, DTS 96/24,
- > DSD Disc (SACD) Playback via HDMI (2.8 MHz/2 ch, 5.1 ch)
- Digital Quad-Core 32-bit DSP (Cirrus Logic) + Aureus™ floating-point
- 192 kHz/24-bit D/A Conversion for Hi-Res Audio
- Enhanced Audio Return Channel (eARC) on HDMI Out (Main)
- Advanced MCACC Auto Room Tuning
 - · Auto Phase Control Plus
 - · Subwoofer EQ
 - Multi-point Standing Wave Control
- > Dirac Live® Room Correction for the full frequency range, 20Hz-20kHz
- Advanced Sound Retriever (2ch)
- Advanced Surround Modes
 - Classical, Unplugged, Entertainment Show, Drama, Advanced Game, Action, Rock/Pop, Sports, Extended Stereo, Mono Music, Front Stage Surround Advance

VIDEO FEATURES

- Support HDMI 2.1*1 with 8K, VRR (Variable Refresh Rate), ALLM (Auto Low Latency Mode), QFT (Quick Frame transport), DSC (Display Stream Compression), and QMS (Quick Media Switching) pass-through
- Supports HDR10+, HDR10, and HLG; 8K/60p (4:2:0/10-bit), 8K/30p (4:4:4/10-bit, 4:2:2/12-bit), 4K/120p (4:4:4/10-bit, 4:2:2/12-bit), 4K60p (4:4:4/12-bit) and BT.2020 colour; DeepColour™ (36-bit), "x.v.Colour", LipSync, and HDCP 2.3

- > Dolby Vision™ Compatible
- > Ultra HD Upscaling (4K to 8K, 1080p to 8K/4K)

HOME NETWORK FEATURES

- > Works with Alexa supporting multi-room music
- Works with OK Google and Chromecast built-in
- DTS Play-Fi with Pioneer Music Control App*3 supporting Hi-Res Audio
- Apple AirPlay 2 with Siri Voice Control
- Works with SONOS supporting multiple Sonos Connect control and Volume Pass Through mode
- Amazon Music HD*3, Spotify, TIDAL, and Deezer Hi-Fi Music-Streaming Services Ready*4
- Internet Radio with TuneIn
- > Hi-Res Audio File Playback via USB/Network
 - Up to 192 kHz/24-bit ALAC*5, AIFF, FLAC, WAV (RIFF) and 11.2 MHz DSD*6

CONVENIENCE FEATURES

- > Personal Preset
- Dialog Enhancement
- > Dual Band (5 GHz/2.4 GHz) 802.11ac Compliant Wi-Fi® Built-in
- Bluetooth® Wireless Technology Transmitter/Receiver (Version: 4.2, Profile: A2DP 1.2/AVRCP 1.3, Codec: SBC/aptX/aptX HD (TX), SBC/ AAC(RX)) Built-In
- Pioneer Remote App*3 Ready for Multi-room Entertainment Control and Network Streaming
- User-Friendly GUI with System Setup Menu
- On-Screen Information for Audio. Video and Network
- Auto Power Off in HDMI Standby Through
- > DAB/FM Tuner 40 Presets
- > User-Friendly Simple Remote Control

FRONT TERMINALS

- USB 1 In for USB Drive
- MCACC/Dirac Live Setup MIC In
- Phones 1 Out

REAR TERMINALS

- HDMI 6 In (4 Assignable)
- HDMI 2 Out (1 for MAIN, 1 for SUB/ZONE 2)
- > Ethernet 1 In
- USB 1 In for USB Drive
- AV (Component) 1 In (Assignable)
- AV (Composite) 2 In (Assignable)

- > Audio 1 In (Assignable)
- > Phono (MM) 1 In
- Digital Coaxial 1 In (Assignable) Digital Optical 1 In (Assignable)
- FRONT, CENTER, SURROUND, HEIGHT 1, SURROUND BACK, SUBWOOFER x 2 Pre Out
- ZONE 2 Pre/Line Out/ZONE B Line Out
- ZONE 3/HEIGHT 2 Pre/Line Out
- Speaker 11ch Out (FRONT, CENTER, SURROUND, HEIGHT 1/ZONE 2/Bi-AMP, SURROUND BACK/ZONE 3/HEIGHT 2)
- IR 1 In/1 Out
- 12 V Trigger 2 Out

- > RS-232C
- > DAB/FM Antenna

SPECIFICATIONS

- > Power Requirements: AC 220-240 V, 50/60 Hz
- Power Consumption/Standby: 850 W/0.1 W
- > Dimensions (W x H x D): 435 x 185 x 386 mm
- > Weight: 13 kg



VSX-LX505(B)/MMP

HDMI 2.1 for a powerful viewing and gaming experience

The VSX-LX505 ensures its HDMI terminals*1 support 8K/60p (4:4:4/12-bit², 4:2:0/10-bit³), 8K/30p (4:4:4/12-bit², 4:4:4/10-bit³, 4:2:2/12-bit), 4K/120p (4:4:4/12-bit², 4:4:4/10-bit³, 4:2:2/12-bit), 4K/120p (4:4:4/12-bit², 4:4:4/10-bit³, 4:2:2/12-bit), 4K/120p (4:4:4/12-bit², 4:4:4/10-bit², 4:2:2/12-bit), 4K/120p (4:4:4/10-bit², 4:4:4/10-bit², 4:2:2/12-bit), 4K/120p (4:4:4/10-bit², 4:4:4/10-bit², 4:2:2/12-bit), 4K/120p (4:4:4/10-bit², 4:4:4/10-bit², 4:4/10-bit², 4:4/10-b bit³, 4:2:0/12-bit) video passthrough to compatible displays, as well as HDCP 2.3°4 so you will have no problem when upgrading to new devices. HDMI 2.1



COMPATIBLE WITH **Dolby** Vision

also supports VRR (Variable Refresh Rate) to eliminate lag, stutter and frametearing to deliver a fluid gaming experience. Various enhancements such as ALLM (Auto Low Latency Mode) and QFT (Quick Frame Transport) help to optimize latency and further limit lag to ensure you'll always be on top of your

game. *1 HDMI 2.1 specification, HDR10+, and passthrough capabilities described are supported on HDMI IN 1-6, HDMI OUT MAIN and SUB/ZONE 2 in sub mode output. *2 DSC signals only. *3 DSC signals only when input via HDMI IN 4-6. *4 All HDMI terminals support HDCP 2.3.

IMAX Enhanced

The VSX-LX505 is IMAX Enhanced, certified to deliver the dynamic and heart-pounding sound presented by DTS just as intended by the filmmaker, and provide an immersive experience on your home theater.



Dolby Atmos®/Dolby Surround Upmixing

By adding an external amplifier, the 9.2ch AV receiver can be expanded to decode 11ch to drive the 7.2.4ch configuration of Dolby Atmos®. You can reproduce object-oriented sound in smooth, curving movements, or the realistic three-dimensional movement overhead by the top speakers. Other audio codecs such as PCM and DSD can be upmixed using Dolby Surround for enjoying 3D surround sound.





DTS:X®/DTS Neural:X Upmixing

DTS:X is the next-generation audio codec from DTS that leverages object-based audio to enable new immersive and interactive audio experiences. By adding an external amplifier, the 9.2ch AV receiver can be expanded to decode 11ch for driving a 7.2.4ch surround system. Experience an immersive soundscape with incredibly rich and life-like audio. Other audio codecs such as PCM and DSD can be upmixed using DTS Neural:X for enjoying 3D surround sound.



7.2.4ch Speaker System



Dolby Atmos Height Virtualization

When playing any Dolby format, engaging the Dolby Atmos Height Virtualizer enables a more immersive listening experience, creating a virtual surround and height effect from traditional speaker layouts without employing additional surround or height speakers.

Apple AirPlay 2

Apple AirPlay 2 lets you effortlessly stream music or podcasts to speakers throughout your house using any Apple device or by asking Siri, and it all stays in perfect sync.



Advanced MCACC Auto Room Tuning featuring Auto Phase Control Plus

Advanced MCACC adjusts the sound according to the listening room and speakers, and also creates clearer sound by suppressing the standing waves that occur between walls or ceiling and floor. Measurement of up to nine positions can be saved for a wide listening area. Auto Phase Control Plus* makes real-time analysis of the phase difference, and automatically compensates the gap between the LFE and main signals, providing strong bass and clear high-frequency sound.

Effectiveness depends on content

Works with SONOS

By bringing the VSX-LX505 into the Sonos eco-system with Connect or Port, you can play any music or audio source on SONOS your Sonos app. With "Volume Pass Through" mode selected at the Sonos App settings, you'll be able to control the volume of the unit by Sonos app or by itself. Enjoy high-quality playback from the AV receiver by Sonos app, just as you would with your favorite Sonos system. *Connection of maximum 3 Sonos devices is supported

Powered Zone 2/Zone 3

With the powered feature, the VSX-LX505 can directly drive speakers in other rooms, without the need for a separate amplifier. What's more, the dedicated DAC for Zone 2 lets you listen to all digital audio sources.





Zone B Output for Wireless Headphones

The VSX-LX505 is equipped with Zone B audio output terminals for expanding the Main Zone sound. You can listen to the sound playing in the living room via wireless headphones.



Voice Control

The VSX-LX505 works wirh Ok Google, so you can control playback of various music services supported by Chromecast by asking a Google Assistant enabled device to play, stop, skip, or take the volume up or down. This receiver also works with Alexa, so you can also use voice commands to control supported music services in mulutiple rooms via Alexa built-in device. Thanks to both voice controls, you can easily operate





and enjoy music services or Internet radio with your voice, without using a remote control or smartphone app.

High Quality Audio transmit by Bluetooth® wireless technology

The VSX-LX505 features built-in Bluetooth® receiver and transmitter. Thus not only can you listen to the sound transmitted from your smartphone or tablet with the AV receiver, but you can also listen to the sound input to the AV receiver from Bluetooth® headphones. Supporting aptX and aptX HD codecs for audio



transmission, you can enjoy high-quality sound with low latency with compatible headphones.

Qualcomm* aptX"HD

Integrated Technologies













































